



FLIR CCTV KEYBOARD

CCTV KEYBOARD FOR UVMS



Key Features:

- Provides control over analog and PC monitors that are connected to a UVMS Control Center application
- Enables control of PTZ cameras with an easy-to-use 3 axis joystick
- Allows for multi-tilt format controls
- Can display and control multiple cameras and devices, including live and recorded video display and alarm management
- Connects via RS- 232 to a UVMS Control Center workstation
- Allows the user to employ a variety of features on UVMS’ Control Center via keyboard shortcuts

www.flir.com/products/cctv-keyboard-for-united-vms

SPECIFICATIONS

Compatibility	UVMS 7.0 and 8.0
Keypanel	Electromechanical
Joystick	3-axis: vector-solving, twisting, return-to-center
Connector	RS232
Display	LCD, 75.2 mm × 33.85 mm
Max. user accounts	1 admin, 10 users
User account types	Admin and user
Power supply	Input 100V ~240V 50 Hz / 60 Hz, Output 12 V DC 1000 mA
Power consumption	Max: 5 W
Operating temperature	-10°C to approx. 55°C (-14°F~131°F)
Operating Humidity	<90% RH
Dimensions	330 × 129 × 102 mm (13 × 5.1 × 4 in)
Weight	2.5 kg (5.5 lbs)
Warranty	1 year
Package dimensions	412 × 208 × 158 mm

To find your local support number, visit: flir.com/contactsupport

www.teledyneflir.com

This product is subject to United States export regulations and may require US authorization prior to export, reexport, or transfer to non-US persons or parties. Diversion contrary to US law is prohibited.

For assistance with confirming the Jurisdiction & Classification of Teledyne FLIR, LLC products, please contact exportquestions@flir.com. ©2023 Teledyne FLIR, LLC. All rights reserved.

Revised 11/03/23
dvt-kbd-g2_Datasheet_112023_RH23-1056-INS